

MDT Switch Actuator 4/8/12-fold with current measurement, MDRC

Version		
AMS-0416.02	Switch Actuator 4-fold	4SU MDRC, 230VAC, 16A, C-Load 140uF, current measurement
AMI-0416.02	Switch Actuator 4-fold	4SU MDRC, 230VAC, 16/20A, C-Load 200uF, current measurement
AMS-0816.02	Switch Actuator 8-fold	8SU MDRC, 230VAC, 16A, C-Load 140uF, current measurement
AMI-0816.02	Switch Actuator 8-fold	8SU MDRC, 230VAC, 16/20A, C-Load 200uF, current measurement
AMS-1216.02	Switch Actuator 12-fold	12SU MDRC, 230VAC, 16A, C-Load 140uF, current measurement
AMI-1216.02	Switch Actuator 12-fold	12SU MDRC, 230VAC, 16/20A, C-Load 200uF, current measurement

The MDT Switch Actuator receives KNX/EIB telegrams and switches up to 12 independent electrical loads. Each output uses a bistable relay and can be operated manually via a push button. A green LED indicates the switching status of each channel.

The outputs are parameterized individually via ETS. The device provides extensive functions like logical operation, status response, block functions, central function, delay functions and staircase lighting function. Additionally the device provides several time and scene control.

The MDT Switch Actuator offers current measurement for each channel and measurement of the total current. In dependence on the parameterization the measured data can be transmit in different data formats (mA/A/kW) onto the KNX bus. Additionally the device provides an hour/service interval meter. The integrated counter allows to capture the power consumption easily. The active power is calculated by the voltage and the factor cos phi.

If the mains voltage fails, all outputs hold their current position. After bus voltage failure or recovery the relay position is selected in dependence on the parameterization.

The MDT Switch Actuator is a modular installation device for fixed installation in dry rooms. It fits on DIN 35mm rails in power distribution boards or closed compact boxes. The MDT Switch Actuator has a separate power supply terminals for each channel.

For project design and commissioning of the MDT Switch Actuator it is recommended to use the ETS or later. Please download the application software at www.mdt.de/Downloads.html

AMS/AMI-04xx.02



AMS/AMI-08xx.02



- Production in Germany, certified according to ISO 9001
- NO and NC contact operation
- Time functions (switch-on/switch-off delay, staircase light function)
- Status response (active/passive) for each channel
- Logical linking of binary data, 8 scenes per channel
- Hour meter
- Central switching functions and llock functions
- Adjustable behaviour in case of bus voltage failure/return
- Separate L- connections
- **Integrated True RMS current measurement (current, kWh)**
- **Current measurement range 10mA-20A**
- **Fast reaction <1s at Master/Slave operation**
- **Integrated counter to capture power consumption (Wh/kWh)**
- Quick application download (long frame support for ETS5)
- Modular installation device for DIN 35mm rails
- Integrated bus coupling unit
- 3 years warranty

Technical Data	AMS-0416.02 AMS-0816.02 AMS-1216.02			AMI-0416.02 AMI-0816.02 AMI-1216.02		
	Number of outputs	4	8	12	4	8
Current measurement range	10 mA - 20 A			10 mA - 20 A		
Measuring inaccuracy	2 %			2 %		
Sampling rate	2000 samples/500 ms			2000 samples/500 ms		
Output switching ratings						
Ohmic load	16 A			16/20 A*		
Capacitive load	140 µF			200 µF		
Voltage	230 V AC			230 V AC		
Maximum inrush current	600 A/150 µs 250 A/600 µs			600 A/150 µs 300 A/600 µs		
Maximum load						
Incandescent lamps	2500 W			3680 W		
Halogen lamps 230V	2500 W			3680 W		
Halogen lamps, electronic transformer**	1500 W			2000 W		
Fluorescent lamps, not compensated	2300 W			3680 W		
Fluorescent lamps, parallel comp.	1300 W			2500 W		
Max. number of electronic transformers	20			28		
Output life expectancy (mechanical)	1.000.000			1.000.000		
Max. total current of the actuator	64 A	96 A	128 A	64 A	96 A	128 A
Spezifikation KNX interface	TP-256 with long frame support for ETS5					
Available application software	ETS 4/5/6 Project file for ETS 3 (*.pr5)			ETS 4/5/6 Project file for ETS 3 (*.pr5)		
Permitted wire gauge						
Screw terminal	1 x (0,5 - 4,0 mm ²) 2 x (0,5 - 2,5 mm ²)			1 x (0,5 - 4,0 mm ²) 2 x (0,5 - 2,5 mm ²)		
KNX busconnection terminal	0,8 mm Ø, solid core			0,8 mm Ø, solid core		
Torque screw terminal	0,5 Nm			0,5 Nm		
Power supply	KNX bus			KNX bus		
Power consumption KNX bus typ.	< 0,3 W	< 0,4 W	< 0,4 W	< 0,3 W	< 0,4 W	< 0,4 W
Operation temperature range	0 to + 45 °C			0 to + 45 °C		
Enclosure	IP 20			IP 20		
Dimensions MDRC (Space Units)	4 SU	8 SU	12 SU	4 SU	8 SU	12 SU

* total current carrying capacity neighbouring outputs max. 32 A

** low voltage halogen lamps with electronic transformer

Exemplary circuit diagram AMS/AMI-0816.02

